Technical Data Sheet sysтем



Box Contents:

System Cabinet | 2 glass shelves | 2x Wall hanging brackets | 4x wall plugs | 4x screws | Instructions booklet

Materials:

Carcass: Extruded Aluminium | Door: Double sided mirror Glass: 3mm PVC Backed

FAQ's:	Units	SYC050	SYC060	SYC100
Important installation requirement	mm	The product must be installed with a minimum distance of 150mm between the infrared sensor and an adjacent wall or obstruction to ensure correct function of the sensor.		
Internal dimensions (L x W x D)	mm	470 x 670 x 111	570 x 670 x 111	970 x 670 x 111
Shelf dimensions (L x W x D)	mm	466 x 100 x 5	566 x 100 x 5	966 x 100 x 5
Max shelf spacing	mm	280		
Distance between door hinges	mm	350		
Individual door dimensions (L x W x D)	mm	500x700x11	299.5x700x11	499.5x700x11
Max door opening angle	0	125 Max		
Max depth with door open	mm	626	425.5	625.5
Hanging bracket centres	mm	282	382	782
What is the thickness of the mirror glass?	mm	3x2		
Is the cabinet IP44 rated?	-	Yes – suitable for use in bathroom zone 2		
What size fuse should I use?	-	Seek the advice of an electrician		
What is the total power consumption?	W	59.1	64.9	86.5
Does the cabinet have an energy rating?	-	Yes – It has an energy rating of: A		
What is the colour of the light and the Kelvin rating?	К	3000-6000		
What is the Lumen of the LEDs?*	Lms	2208	2448	3168
What is the wattage of the lights?	W	16.6	18.4	24
Where is the IR sensor/rocker switch located?	-	Underneath - Right Hand Side		
Where is the shaver socket located?	-	Inside on the top right		
Can the LED lighting be replaced?	-	No**		
Can the IR sensor be replaced?	-	No		
What is the output of the demister pad?	W	12	16	32
What are the dimensions of the demister pad?	mm	400 x 150	400 x 150	400 x 300
How do I turn on the demister pad?	-	The demister pad will turn on when the LEDs are turned on.		
Are illuminated cabinets supplied with mains cable?	-	All illuminated cabinets are supplied with a removeable 500mm main		

 Are infinitiated cabinets supplied with mains cable?
 cable. There is ample storage for excess cable in the back of the unit.

 Dimensions are subject to change; customers are advised to measure actual product before commencing installation.

Fixing point dimensions are for guidance only/the positions of wall fixing must be checked when product is received. *The Lumen represents the output of the LED. This may vary depending on the diffuser material i.e., glass or acrylic. **The LEDs are not replaceable to maintain the integrity of the product's resistance to moisture ingress

Roper Rhodes, Brassmill Lane Trading Estate, Bath BA1 3JF TEL: 01225 303 900 | techsupport@roperrhodes.co.uk www.RoperRhodes.co.uk

ROPER RHODES[®]



<u>SYC060</u>



<u>SYC100</u>



Roper Rhodes, Brassmill Lane Trading Estate, Bath BA1 3JF TEL: 01225 303 900 | techsupport@roperrhodes.co.uk www.RoperRhodes.co.uk